MP-S201

Masterpiece Stereo Amplifier







MP-S201

Masterpiece Stereo Amplifier

THD + noise

The MP-S201 is a true masterpiece in every sense of the word.

One of the first things we were told, when we introduced the ideas behind the MP-S201, was "Mission Impossible" But for the Vitus Audio team of engineers and workers such statement, is what brings out the teams enthusiasm and hereafter the hard work began.

While we maintain our "Signature" design, which we have acheived massive recognition for world wide, we have stepped it up a notch.

Special tools were needed for even considering manufactoring this +125kg amplifier and it's colossal size - as we refuse to compromise on the fact, that it is HANDMADE in Denmark.

While intended for being a stereo power amplifier, monomode is made available too, should bi-amping be required.

Technical keywords:

- 1. 4.5KVA UI transformers with <2% loss
- 2. 1.200.000uF capacitor bank
- 3. Zero global negative feedback
- 4. 2mm thick boards with 105um copper on all layers
- 5. Digital control circuitry completely separated with its own power supply starting with a separate power cord
- 6. Modul based for future upgradability.
- 7. Stillpoint Ultra 5 feet standard

For the early listeners, the imidiate reaction was, "it has no peer"

INPUT	XLR stereo	XLR mono	
Available	2 (1 pr ch)	1	
Sensitivity	0,7 Vrms	0,7 Vrms	
Impedance	10ΚΩ	10ΚΩ	
OUTPUT	Speaker L	Speaker R	
Available	1	1	
Impedance	$75\text{m}\Omega$	75 mΩ	
Power W (8/4 Ω)	700/1400	700/1400	Class AB
Power W (8/4 Ω)	25/50	25/50	Class A
Frequency response	+800kHz	+800kHz	
Signal to noise ratio	>130dB	> 130dB	

POWER CONSUMPTION		
<1W		
550W _{RMS}		
430 mm		
505 mm		
708 mm		
125 Kg		

> 0,01%

> 0,01%



